

SIM Card Installat on DT301Y/ DT311Y

- 1 Make sure the tablet is completely powered off. Take the handstrap off of the back of the tablet for easier access to the SIM socket.



DT301Y - back



DT311Y - back



- 2 Remove the LTE/SSD module compartment cover screws:
6x for DT301Y, 10x for DT311Y.
- 3 Gently take the cover off. There is one back battery and Wifi switch attached to this cover. Do not pull off the backup battery cable or any cable off of the board. Set the cover aside towards the left side (see picture). The SIM card slot is located underneath the Sierra Wireless module.



- 4 Carefully place the end of the SIM card under the PCI-E store module (see picture).



- 5 Then slide in the SIM card into the slot (see picture).



- 6 Push the SIM card in until you hear a click. Push it in slightly again to release it (push to lock, push again to unlock). Since there is limited room between the storage module and the SIM slot, you may use a piece of invisible tape and stick the SIM to it so it can be easily removed, once it is completely out of the SIM slot.
- 7 Put the compartment cover and screws back. Finally put the hand strap back.